SCENEMAKER 1232

12 Fixtures x 32 Channels DMX Intelligent Lighting Controller

SCENEMAKER 1232 is a universal intelligent lighting controller. It allows you to manage up to 12 fixtures composed of 32 channels each (384 channels in total), and up to 240 programmable scenes. 6 chases can contain up to 240 steps composed by the saved scenes (the steps) and in any order. Programs can be triggered by music, MIDI, automatically or manually. On the surface you will find various programming tools such as 16 universal channel sliders, quick access scanner and scene buttons, and a LED display indicator for easier navigation of controls and menu functions.







PRODUCT DETAILS

Key features

- 12 Fixtures with 16 DMX Channels each; 192 Channels in total
- 30 banks of 8 programmable scenes, 240 scenes total
- 6 chases of 240 programmed scenes from 30 bank
- Executes multiple chases simultaneously
- 16 Sliders for direct control of channels
- Auto Mode controlled by Speed and Fade Time
- Master Blackout
- Built-in microphone for Music triggering
- LED Display for easy navigation of menus
- MIDI control over banks, chases and Blackout
- USB LED Goose-neck Lamp INCLUDED
- Plastic end housing

Specifications

Power Supply	DC 9V-12V, 1000mA min.
USB Lamp	5V - 200 mA max
Protocols	DMX-512 USITT
Data Input	locking 3-pin XLR male socket
Data Output	locking 3-pin XLR female socket
Data Pin Configuration	Pin 1 shield, Pin 2 (-), Pin 3 (+)
Controller Size (WxHxD)	520 x 73 x 183 mm
Net Weight 3.0 kg	
Packing Dimension (WxHxD)	620 x 135 x 235 mm
Packing Gross Weight	3.7 kg