

30W USB Charging Adaptor

Description.

This USB Charger is compatible with portable devices such as smart phones, tablets and other such devices that require charging via a USB Type A and Type C ports

Programmable Power Supply (PPS) charging prolongs battery life and makes charging more efficient.

Features

- Robust design that fits comfortably in the hand
- Dual USB 30W 1 x A + 1 x C ports
- Fast Charger with Power Delivery and Quick Charge Protocols
- Easily charge multiple devices simultaneously using intelligent charging technology
- PPS Programmable Power Supply technology

Technical Information

Input		100-250V~ 50Hz 0.8A Max					
USB Output	Device Voltage:	5VDC	9VDC	12VDC	15VDC	20VDC	PPS: 3.3-11VDC
	USB-C: (Max.)	3.0A, 15.0W	3.0A, 27.0W	2.5A, 19.9W	2.0A, 30.04W	1.5A, 30.0W	3.0A, 33.0W
	USB-A: (Max.)	3.0 A, 15.0W	3.0 A, 27.0W	2.5A, 18.0W	2.0A, 30.0W	1.5A, 30.0W	n/a
	USB-C + USB-A (Max.)	3.6A, 18.0W	n/a	n/a	n/a	n/a	n/a
Average Active Efficiency		84.2%					
Efficiency at Low Load (10%)		80.1%					
No-load Power Consumption		0.08W					
Warranty		2 Years					

Range

30W USB Charging Adaptor	TP6102

Compliance

BS 1363-2
BS EN IEC 62368-3

Deta Electrical Company Ltd.
UK: Panattoni Park Luton Road Chalton Bedfordshire LU4 9TT UK
EU: Unit 16 Ashbourne Industrial Estate Ashbourne Co. Meath A84 W972 Ireland
Tel. +44 1582 544 548 technical@deta.co.uk