Inline LED Dimming Driver Power Supply Series

Input 12vdc to 24vdc

Part number TGR-DIAL-DIM-2A (Black version) TGR-DIAL-DIM-2A-W (White version)



- Input voltage: DC 12V / 24V
- **Output power: 2A (Max. 24W at 12vdc / Max 48W at 24vdc)**
- Output Signal PWM
- Simply turn dial to adjust brightness of LED light and turn on or off
- No battery required
- A constant voltage power supply will be needed to provide the 12vdc or 24vdc input. The output volt-age supplied by this unit will be the same as the input voltage so make sure the correct PSU is selected for your LED strip
- Length 30cm (body 25mm x 66mm x 30mm)
- Industry Standard 2.1mm input socket to a standard 2.1mm DC connector. Widely compatible

Part number TGR-TOUCH-DIM (Black version) TGR-TOUCH-DIM-W (White version)



- Input voltage: DC 12V / 24V
- **Output power: 5A (Max. 60W at 12vdc / Max 120W at 24vdc)**
- Output Signal PWM
- Simply touch to adjust brightness of LED light and turn on or off (quick tap to turn on or off and long touch and hold to adjust brightness)
- No battery required
- A constant voltage power supply will be needed to provide the 12vdc or 24vdc input. The output volt-age supplied by this unit will be the same as the input voltage so make sure the correct PSU is selected for your LED strip
- Length 30cm (body 25mm x 66mm x 30mm)
- Industry Standard 2.1mm input socket to a standard 2.1mm DC connector. Widely compatible